


ZUBEHÖR/SONSTIGE: DRIVER LC38W 1050MA 7,5V-36,2V 8W-38W ON/OFF



800-1220

MOUNTING

Mounting location: -
Type: -

DIMENSION

Length/Width: 160x82 mm
Height: 34 mm
Weight (net): 0.2 kg

ORDER NUMBER

800-1220

TECHNICAL DESCRIPTION

Height: 34 mm · Length: 160 mm · Width: 82 mm



Date: 06/15/2026

We reserve the right to make technical changes without prior notice.

PROLICHT GmbH | Austria | 6091 Götzens | Gewerbepark 9

T +43 5234 33 499 | F +435234 33 499-22 | info@prolicht.at | www.prolicht.at

LUMINAIRES PER CIRCUIT BREAKER TYPE

Type	B10	B13	B16	B20	C10	C13	C16	C20
#	35	46	56	70	36	46	56	70

This table provides an overview of different types of circuit breakers and the maximum number of lamps that can be connected to each breaker type. The permissible number depends on the characteristics of the circuit breaker (e.g., Type B, C, or D) as well as the power consumption and inrush current of the lamps used. These values serve as a reference for planning electrical installations in lighting applications.